# Quick Installation Instructions for NVR

## 1. HDD Installation

1. Ensure Power supply has been disconnected, open the case cover;



2. Fx the HDD in the case;



3. Connect HDD data line, power line ;



4. Install the cover.



#### 2. Device Connection

After HDD installation, connect the Device as follows:



#### 3. Login

After the Devices connected, Press the power button "————————, then the NVR booting, Enter the usename and password login the system. The defult username is" admin", password is "".



## 4. Connect IPC Devices

1. Right click|System Setup|Net Settin| Connection set the IP of this NVR;

Connection	×
IP	192.168.16.169
NetMask	255.255.255.0
GateWay	192,168,16.1
DNS	202.102.128.68
MAC	E0:62:90:E0:3C:D9
Automatic(DHCP)	
Device Port	9101
NVSIP	A225613087
Status	Online
	Apply OK Cancel

2. Right click IP Camera, click [search], then can search the IP Camera in this lan;

ova	reneurir came	10				
NO.	NVSIP	Devic	e Name	IP		
1	N5037626	MyCa	imera	192.168.16.99	s	earch
2	A109612283	HD IF	°C	192.168.11.100		
3	A166117729	不要	<b>新聞81</b>	192.168.13.208		Add
4	A159730693	HD IF	°C	192.168.16.106		
5	A159812075	HD IF	°C	192,168,13,209		Add All
6	N184879632	H.264		192,168,16,35		
7	A185392182	HD IF	C	192.168.10.6		
8	A196497577	HD IF	C-1080p	192.168.13.102	1	
Add	ed IPCamera	You can add n Device Name	nore,2 1080P	or 4 960P or 4 720P IP Status		emove
Add Chr	ed IPCamera NVSIP	You can add n Device Name	nore,2 1080P	or 4 960P or 4 720P IP Status		emove
Add Chri 1	ed IPCamera NVSIP	You can add n Device Name	nore,2 1080P IP	or 4 960P or 4 720P IP Status No Video No Video	Rei	emove move A
Add Chn 1 2 3	ed IPCamera I NVSIP	You can add n Device Name	nore,2 1080P IP	or 4 960P or 4 720P IP Status No Video No Video No Video	Re	emove move A
Add Chri 2 3 4	ed IPCamera I NVSIP	You can add n Device Name	nore,2 1080P IP	or 4 960P or 4 720P IP Status No Video No Video No Video No Video	Re	emove move A etwork
Add Chri 2 3 4	ed IPCamera 1 NVSIP	You can add n Device Name	nore,2 1090P IP	or 4 960P or 4 720P IP Status No Video No Video No Video No Video	Re	emove move A etwork Set
Add Chri 2 3 4	ed IPCamera I NVSIP	You can add n Device Name	nore,2 1080P IP	or 4 960P or 4 720P IP Status No Video No Video No Video No Video	Re	emove move A etwork Set Exit
Add Chn 1 2 3 4	ed IPCamera I NVSIP	You can add n Device Name	nore,2 1080P	or 4 960P or 4 720P IP Status No Video No Video No Video	Rei	emove move A etwork Set Exit

3. Click any ip camera, click button [Add], can put this ip camera into the right device list, and connected successful; Click the button [Add All], can put all ip camera into the right device list, and connected all successful.

Jea	cheun-came				
NO.	NVSIP	Devic	e Name	IP.	
1	N6037626	MyCa	mera	192.168.16.99	Search
20	A156117729	不要	ESKB1	192 168 13 208	
3	A159730693	HDIP	c	192.168.16.105	Add
4	A159012075	HDIP	C	192.168.13.209	Contraction of the local division of the loc
6	N184879632	H.264		192.168.16.36	Add All
6	A185392182	HDIP	C	192.168.10.6	
7	A196497577	HDIP	C-1080p	192,168,13,102	
8	A196500336	1090-	1	192 168 13 111	
Add	ed IPCamera	You can add n Device Name	nore,1 1080P or	2 960P or 3 720P IP Status	Remove
Add	ed IPCamera NVSIP A109612283	You can add n Device Name HD IPC	nore,1 1080P or IP 192,166,11 10	2 960P or 3 720P IP Status 0 Connected	Remove
Add Chri 1	ed IPCamera NVSIP A109612283	You can add n Device Name HO IFC	nore,1 1080P or IP 192,166,11,10	2 960P or 3 720P IP Status O Connected No Video	Remove
Add Chri 2 3	ed IPCamera NVSIP A109612283	You can add n Device Name HO IPC	nore,1 1090P or IP 192,168,11.10	2 960P or 3 720P IP Status 0 Connected No Video No Video	Remove Remove A
Add Chn 2 3 4	ed IPCamera NVSIP A109612283	You can add m Device Name HD IPC	nore,1 1090P or IP 192,166,11,10	2 960P or 3 720P IP Status 00 Connected No Video No Video No Video	Remove Remove A Network
Add Chri 2 3 4	ed IPCamera NVSIP A109612283	You can add n Device Name HO IPC	lore,1 1090P or IP 192,166,11,10	2 960P or 3 720P IP Status 00 Connected No Video No Video No Video	Remove Remove A Network Set
Add Chri 2 3 4	ed IPCamera NVSIP A109612283	You can add m Device Name HD IPC	nare,1 1080P or IP 192,166 11 10	2 960P or 3 720P IP Status 10 Connected No Video No Video	Remove Remove A Network Set Exit
Add Chri 2 3 4	ed IPCamera NVSIP A109612283	You can add n Device Name HD IPC	nore,11090P or IP 1921661110	2 960P or 3 720P IP Status 0 Connected No Video No Video No Video	Remove Remove A Network Set Exit

Unconnect setps:

Click any ip camera of the right device list,Click [Remove],can unconnected this connection.Click [Remove All],can unconnect all connection.

#### 5. Remote Connection with CMS

Open CMS, in the login interface, select "Device ID Login", Enter the Device ID, Click Advanced button, Enter the network username and password, Click Login button, then can login successful and connected the NVR Device.



### 6. Remote Connection with IE

Open IE with Http://www.nvsip.com ,select "Device ID", Enter the Device ID, and the network username and password, Click the [Login] button, then can login the IE

system and connected the NVR Device.



## 7. Remote Connection with Mobile Phone

1. Download the APP and install it ,after installation, register a user, the login with this user.

att	中国联通 令 下午2:31
	, № 342408456
	•••••
	Login
	Modify Register
	Local login

2. After Login, Click the button<sup>+</sup>, Add Device, Enter the Device ID and network username and password.



2. Click [Save] button, then Add this Deviec successful.





