

LM576R Laser Level User Manual

Preface

Thank you for purchasing this brand new LM576R laser level. In order to use this product safely and correctly, please read this manual thoroughly, especially the Safety Instructions part.

After reading this manual, it is recommended to keep the manual at an easily accessible place, preferably close to the device, for future reference.

Limited Warranty and Liability

Uni-Trend guarantees that the product is free from any defect in material and workmanship within one year from the purchase date. This warranty does not apply to damages caused by accident, negligence, misuse, modification, contamination and improper handling. The dealer shall not be entitled to give any other warranty on behalf of Uni-Trend. If you need warranty service within the warranty period, please contact your seller directly.

This warranty is the only compensation you can obtain. Uni-Trend will not be responsible for any special, indirect, incidental or subsequent damage or loss caused by any reason or speculation. As some areas or countries do not allow limitations on implied warranties and incidental or subsequent damage, the above limitation of liability and stipulation may not apply to you.

1. Product Structure



2. Safety Instructions

Before using this product, please carefully read and follow the user manual and safety instructions.

Warning! <ul style="list-style-type: none">● Class 2 laser product● Wavelength: 635nm±10nm
Laser radiation: <ul style="list-style-type: none">● Do not stare into beam● Do not directly expose to eyes● Avoid using optical instruments

3. Cautions

Some product kits will provide glasses. Please note that these glasses are not safety glasses. They are only used to help users recognize the laser beam in strong ambient light or when the light source of the laser instrument is distant.

Do not stare into beam or directly observe the laser beam via an optical instrument or set the instrument at the eye level (to avoid damage to eyes).

- Do not disassemble the laser instrument without authorization.
- Do not refit the instrument without authorization in any way; otherwise it may cause harmful laser radiation exposure.
- Do not use the laser instrument around children or allow them to use it.
- Exposure to Class 2 lasers for no more than 2 seconds is generally considered safe, because natural eyelid reflexes (blinking) usually can provide adequate protection.

4. Operation Guidelines

- When the laser instrument is in the locked state, toggle the pendulum lock to the unlocked position to start the self-inspection. After completing the self-inspection, the horizontal laser line is always on, and the instrument is in the self-leveling mode. In the self-leveling range of 3°±1°, the instrument will perform the self-leveling function. If the range is exceeded, the instrument will flash quickly and make a beeping sound.
- Press the H button to turn on/off the horizontal laser line, and press the V button to turn on/off the vertical laser line. (The two horizontal/vertical laser lines can be used alone or together).
- When the instrument is turned on, toggle the pendulum lock to the locked position again, and the instrument can be turned off.
Note: It is to ensure that users must toggle the pendulum lock to the locked position before turning off the instrument.
- When the instrument is in use, the charging/power indicator is off. When the battery power is 20% remaining, the right indicator light of the control panel battery icon flashes blue, and the instrument will automatically shut down after it is fully discharged. When the battery pack is being charged, the charging/power indicator will flash in red color to remind users that the instrument is being charged. When fully charged, the charging/power indicator will switch to a steady green state. When directly using the charging interface on the instrument to charge, the green light will flash, and when it is fully charged, the indicator will switch to a steady green state.
Long press the V button or use the remote control to adjust the laser line brightness (three scales).

5. Manual Mode

When the instrument is turned off, press and hold the V button for more than 3 seconds to enter the manual mode. At this time, the instrument is turned on and emits a horizontal laser line. The lock indicator is always on, and the laser line will flash once every five seconds to remind users that it is in the manual mode. The laser line can be set to different angles. In the manual mode, press and hold the V button again for more than 3 seconds, or toggle the pendulum lock to enter the self-leveling mode and then toggle it again to shut down.

Note: The laser line in the manual mode cannot be used as a horizontal/vertical reference line.

6. Remote Control Mode

This product is equipped with a remote control chip, which can remotely switch the functions of the instrument via the equipped remote control. Pairing is required when using the remote control for the first time. Turn on the instrument first and then press and hold the H button of the instrument and the H button of the remote control simultaneously for more than 3 seconds to successfully pair.

Note: The remote control function can only be used after the instrument is turned on. The remote control can only switch functions, and cannot remotely turn on/off the instrument. The brightness can be adjusted by using the remote control after the instrument is turned on or in the manual mode.

7.Specifications

Model	LM576R
Laser tube	SHARP LD
Laser type	Red, high brightness
Laser lines	16 lines
Laser wavelength	635nm±10nm
Laser class	CLASS II
Horizontal accuracy	±3mm/10m
Vertical accuracy	±3mm/10m
Brightness adjustment	3 scales adjustable
Laser linewidth	5mm±1/10m (indoor lighting: 80~100lux)
Emission angle	360°
Leveling range	±(3±1)°
Minimum distance to wall/ground	Wall: 10mm, ground: 15mm
Battery life	> 30h
Operating range	In the highest brightness, radius > 30m
Leveling modes	Magnetic damping, heavy hammer
Alarm modes	Buzzer + laser line flashes
Diagonal mode	√
Product size	135×87×150mm
Operating temperature	-10~50℃
Power supply	3.7V 6000mAh
Standard accessories	Laser level, 6000mAh battery pack, Type-C cable, user manual, Wall-mounted bracket+iron plate , remote control, toolbox

8. Accessories

Laser level-----	1 PC
Remote control-----	1 PC
6000mAh lithium battery-----	1 PC
User manual-----	1 PC
Wall-mounted bracket+iron plate -----	1 PC
Type-C charging cable-----	1 PC
Toolbox-----	1 PC

UNI-T®
UNI-TREND TECHNOLOGY (CHINA) CO., LTD.
No.6, Gong Ye Bei 1st Road,
Songshan Lake National High-Tech Industrial
Development Zone, Dongguan City,
Guangdong Province, China